







# **LED HEX PAR 12**

#### LEDNIT122

### Rugged LED washlight, featuring:

- 12 x 10W Hex-color RGBAW+UV LED
- Die-cast housing for efficient cooling and road-worthy durability
- High-frequency LED modulation for flicker-free video playback
- Four selectable dimming curves
- Gel frame and gel frame holder included
- Power In and Out connections for linking multiple units
- Built-in sound-active and auto (stand-alone) programs
- USB port for optional UFI wi-fi transceiver for wireless app control
- Infrared sensor for optional IR6 remote control





## **Specifications**

| Product           | LED HEX PAR 12            |
|-------------------|---------------------------|
| Code              | LEDNIT122                 |
| Lamp Source       | 12 x 10W RGBAW+UV LED     |
| Power Supply      | 100-240V AC, 50/60Hz      |
| Power Consumption | 83W                       |
| DMX Connection    | 3-pin XLR In/Out          |
| DMX Channels      | 6/11                      |
| Beam Angle        | 25°                       |
| Output            | 350 lux @ 5m              |
| Dimensions        | 253(L) x 290(W) x 98(H)mm |
| Weight            | 3.2kg                     |

#### **Channel Allocation**

|    | 6-CH  | 11-CH  |
|----|-------|--|
| 1  | Red   | Red  |
| 2  | Green | Green  |
| 3  | Blue  | Blue   |
| 4  | Amber | Amber  |
| 5  | White | White  |
| 6  | UV    | UV   |
| 7  |       | Color Macros                                     |
| 8  |       | Strobe / Speed / Sound Sensitivity               |
| 9  |       | Pulse effects / Color Fade & Snap / Sound-active |
| 10 |       | Dimmer   |
| 11 |       | Dimmer Speed (curve selection)                   |
|    |       |  |





www.showtech.com.au